



VAN MEDEVOORT

CD 350

CD - SACD PLAYER



Features:

- plays two channel CD and SACD
- excellent digital-analog converters
- highly musical performance with low distortion
- digital outputs - coaxial and optical for CD
- special vM super clock and audio circuitry for optimal soundstage
- RCA gold plated analog output connectors, XLR optional
- remote controlled
- silver / black finished front plate

The Van Medevoort CD350 stereo CD and SACD player is designed to match the vM amplifiers. The same heavy, rigid housing is used to minimize resonances and mechanical distortion. The CD transport mechanism is mounted using an elastic suspension to isolate against acoustic feedback. Only audiophile quality components are used for the digital and analog circuits. Extra control options are available, such as repeat or random play, by using the remote control. Next to the optical, digital and analog coaxial outputs, there is optional also a balanced XLR analog output possible for optimal connection via XLR cables.

Specifications:

format CD / SACD	16 bit PCM / 1 bit DSD
frequency response CD / SACD	2-20,000 Hz / 100,000 Hz
dynamic range	> 100 dB / 114 dB
distortion	< 0.002 % / 0.0009 %
signal to noise ratio	> 103 dB
channel separation	> 100 dB
outputs / connectors	4 / 2x RCA + Optical
output analog / digital	2.2 Vrms / 0.5 Vp-p (CD)
power supply	115-230 Volt / 50-60 Hz
power consumption	20 Watt
weight	9 kg
size w x h (h+feet) x d	434 x 88 (102) x 390 mm

Options: vM Silver Cable  
XLR output

**Audioart**  
AUDIO PRODUCTS

Visit our website for more information.  
[www.vanmedevoort.com](http://www.vanmedevoort.com)  
Copyright © 2007 Audioart / The Netherlands  
Specifications are subject to change without prior notice.

Herenweg 15, NL-3602 AM  
Maarssen, The Netherlands  
Tel.: +31 (0)346 59 02 90  
Fax: +31 (0)346 59 01 03  
Website: [www.audioart.nl](http://www.audioart.nl)  
E-mail : [info@audioart.nl](mailto:info@audioart.nl)